CHI MEI
OPTOELECTRONICS CORP.

TFT LCD Approval Specification

MODEL NO.: M170E7-L02

Customer: _____

Approved by: _____

Note:

Liquid Crystal Display Division	
QRA Division	OA Head Division
Approval	Approval

- CONTENTS -

Version 2.0

Issued Date: Mar. 08, 2006
Model No.: M170E7-L02

Approval

REVISION HISTORY

Version	Date	Section	Description
Ver. 2.0	Mar. 08, 06	-	M170E7-L02 Approval specification was first issued.

Version 2.0

Approval

1. GENERAL DESCRIPTION

1.1 OVERVIEW

The M170E7-L02 model is a 17.0 inch TFT-LCD module with a 4-CCFL Backlight Unit and a 30-pin 2ch-LVDS interface. This module supports 1280 x 1024 SXGA mode and displays 16.2M colors. The inverter module for the Backlight Unit is not built in.

1.2 FEATURES

- Extra-wide viewing angle

- Super high contrast ratio

- Super fast response time

- High color saturation (EBU Like Specifications)

- SXGA (1280 x 1024 pixels) resolution

- DE (Data Enable) only mode

- LVDS (Low Voltage Differential Signaling) interface

- Compact size and slim border

- RoHS compliance

- TCO'03 compliance

1.3 APPLICATION

- TFT LCD Monitor

1.4 GENERAL SPECIFICATI0NS

Item	Specification	Unit	Note
Active Area	337.92 (H) x 270.34 (V) (17.0" diagonal)	mm	(1)
Bezel Opening Area	340.92 (H) x 273.34 (V)	mm	
Driver Element	a-si TFT active matrix	-	-
Pixel Number	1280 x R.G.B. x 1024	pixel	-
Pixel Pitch	0.264 (H) x 0.264 (V)	mm	-
Pixel Arrangement	RGB vertical stripe	-	-
Display Colors	16.2M	color	-
Transmissive Mode	Normally white	-	-
Surface Treatment	Hard coating (3H), AG (Haze 25%)	-	-

1.5 MECHANICAL SPECIFICATIONS

Item		Min.	Typ.	Max.	Unit	Note
Module Size	Horizontal(H)	354.42	354.92	355.42	mm	(1)
	Vertical(V)	289.84	290.34	290.84	mm	
	Depth(D)	-	12.8	13.3	mm	
Weight		-	1825	1895	g	-
I/F connector mounting position		The mounting inclination of the connector makes the screen center within ±0.5mm as the horizontal.				(2)

Note (1) Please refer to the attached drawings for more information of front and back outline dimensions.

Version 2.0

Approval

2. ABSOLUTE MAXIMUM RATINGS

2.1 ABSOLUTE RATINGS OF ENVIRONMENT

Item	Symbol	Value		Unit	Note
		Min.	Max.		
Storage Temperature	T_{ST}	-20	60	ºC	(1)
Operating Ambient Temperature	T_{OP}	0	50	ºC	(1), (2)
Shock (Non-Operating)	S_{NOP}	-	50	G	(3), (5)
Vibration (Non-Operating)	V_{NOP}	-	1.5	G	(4), (5)

Note (1) Temperature and relative humidity range is shown in the figure below.

(a) 90 %RH Max. (Ta $\leq$ 40 ºC).

(b) Wet-bulb temperature should be 39 ºC Max. (Ta > 40 ºC).

(c) No condensation.

Note (2) The temperature of panel display surface area should be 0 ºC Min. and 60 ºC Max.

Relative Humidity (%RH)

Temperature (ºC)

Note (3) 11ms, half sine wave, 1 time for ± X, ± Y, ± Z.

Note (4) 10 ~ 300 Hz, 10min/cycle, 3 cycles each X, Y, Z.

Note (5) At testing Vibration and Shock, the fixture in holding the module has to be hard and rigid enough

so that the module would not be twisted or bent by the fixture.

The fixing condition is shown as below:

Version 2.0

Issued Date: Mar. 08, 2006
Model No.: M170E7-L02

Approval

2.2 ELECTRICAL ABSOLUTE RATINGS

2.2.1 TFT LCD MODULE

| Item	Symbol	Value		Unit	Note
		Min.	Max.		
Power Supply Voltage	Vcc	-0.3	+6.0	V	(1)
Logic Input Voltage	V_{IN}	-0.3	4.3	V	

2.2.2 BACKLIGHT UNIT

Item	Symbol	Value		Unit	Note
		Min.	Max.		
Lamp Voltage	V_L	-	2.5K	V_{RMS}	(1), (2), I_L = 7.0 mA
Lamp Current	I_L	2.0	7.5	mA_{RMS}	(1), (2)
Lamp Frequency	F_L	40	80	KHz	

Note (1) Permanent damage might occur if the module is operated at conditions exceeding the maximum

values.

Note (2) Specified values are for lamp (Refer to 3.2 for further information).

Version 2.0

Issued Date: Mar. 08, 2006
Model No.: M170E7-L02

Approval

3. ELECTRICAL CHARACTERISTICS

3.1 TFT LCD MODULE

Ta = 25 ± 2 ºC

Parameter		Symbol	Value			Unit	Note
			Min.	Typ.	Max.		
Power Supply Voltage		Vcc	4.5	5.0	5.5	V	-
Ripple Voltage		V_{RP}	-	--	100	mV	-
Rush Current		I_{RUSH}	-	--	3.8	A	(2)
Power Supply Current	White	Icc	-	420	590	mA	(3)a
	Black		-	790	1100	mA	(3)b
	f_V = 75Hz, Vcc=4.5V		-	-	1260	mA	(4)
LVDS differential input voltage		Vid	-100	-	+100	mV	
LVDS common input voltage		Vic	--	1.2	--	V	

Note (1) The module is recommended to operate within specification ranges listed above for normal function.

Note (2) Measurement Conditions:

Vcc rising time is 470μs

Version 2.0

Approval

Note (3) The specified power supply current is under the conditions at Vcc = 5.0 V, Ta = 25 ± 2 ºC, f_v = 60 Hz, whereas a power dissipation check pattern below is displayed.

a. White Pattern   b. Black Pattern

Active Area   Active Area

Note (4) The specified power supply current is under the conditions at Vcc = 4.5 V, Ta = 25 ± 2 ºC, f_v = 75 Hz, whereas a power dissipation check pattern (Black Pattern) below is displayed.

Black Pattern

Active Area

Version 2.0

Issued Date: Mar. 08, 2006
Model No.: M170E7-L02

Approval

3.2 BACKLIGHT UNIT

Parameter	Symbol	Value			Unit	Note
		Min.	Typ.	Max.		
Lamp Input Voltage	V_L	576	640	704	V_{RMS}	I_L = 7.0 mA
Lamp Current	I_L	2.0	7.0	7.5	mA_{RMS}	(1)
Lamp Turn On Voltage	V_S	-	-	1250(25 ^{o}C)	V_{RMS}	(2)
		-	-	1470 (0 ^{o}C)	V_{RMS}	(2)
Operating Frequency	F_L	40	-	80	KHz	(3)
Lamp Life Time	L_{BL}	50,000	-	-	Hrs	(5) I_L = 7.0 mA
Power Consumption	P_L	-	17.92	-	W	(4), I_L = 7.0 mA

Note (1) Lamp current is measured by utilizing high-frequency current meters as shown below:

Ta = 25 ± 2 ºC

Note (2) The voltage that must be larger than Vs should be applied to the lamp for more than 1 second after startup. Otherwise, the lamp may not be turned on normally.

Note (3) The lamp frequency may produce interference with horizontal synchronization frequency from the display, which might cause line flow on the display. In order to avoid interference, the lamp frequency should be detached from the horizontal synchronization frequency and its harmonics as far as possible.

Note (4) $P_L = I_L \times V_L \times 4$ CCFLs

Note (5) The lifetime of lamp can be defined as the time in which it continues to operate under the condition Ta = 25 ±2 ^{o}C and **I_L = 7.0 mArms** until one of the following events occurs:

(a) When the brightness becomes or lower than 50% of its original value.

(b) When the effective ignition length becomes or lower than 80% of its original value. (Effective ignition length is defined as an area that has less than 70% brightness compared to the brightness in the center point.)

Note (6) The waveform of the voltage output of inverter must be area-symmetric and the design of the inverter must have specifications for the modularized lamp. The performance of the Backlight, such as lifetime or brightness, is greatly influenced by the characteristics of the DC-AC inverter for the lamp. All the parameters of an inverter should be carefully designed to avoid producing too much current leakage from high voltage output of the inverter. When designing or ordering the inverter please make sure that a poor lighting caused by the mismatch of the Backlight and the inverter (miss-lighting, flicker, etc.) never occurs. If the above situation is confirmed, the module should be operated in the same manners when it is installed in your instrument.

Version 2.0

Issued Date: Mar. 08, 2006
Model No.: M170E7-L02

Approval

The output of the inverter must have symmetrical (negative and positive) voltage waveform and symmetrical current waveform.(Unsymmetrical ratio is less than 10%) Please do not use the inverter which has unsymmetrical voltage and unsymmetrical current and spike wave. Lamp frequency may produce interface with horizontal synchronous frequency and as a result this may cause beat on the display. Therefore lamp frequency shall be as away possible from the horizontal synchronous frequency and from its harmonics in order to prevent interference.

Requirements for a system inverter design, which is intended to have a better display performance, a better power efficiency and a more reliable lamp. It shall help increase the lamp lifetime and reduce its leakage current.

a. The asymmetry rate of the inverter waveform should be 10% below;

b. The distortion rate of the waveform should be within $\sqrt{2} \pm 10\%$;

c. The ideal sine wave form shall be symmetric in positive and negative polarities.

* Asymmetry rate:

$$| I_p - I_{-p} | / I_{rms} * 100\%$$

* Distortion rate

$$I_p \text{ (or } I_{-p}) / I_{rms}$$

Version 2.0

Issued Date: Mar. 08, 2006
Model No.: M170E7-L02

Approval

4. BLOCK DIAGRAM
4.1 TFT LCD MODULE

4.2 BACKLIGHT UNIT

1 HV(Pink)
2 LV(White)
1 HV(Blue)
2 LV(Black)

1 HV(Pink)
2 LV(White)
1 HV(Blue)
2 LV(Black)

Version 2.0

Issued Date: Mar. 08, 2006
Model No.: M170E7-L02

Approval

5. INPUT TERMINAL PIN ASSIGNMENT

5.1 TFT LCD MODULE

Pin	Name	Description
1	RXO0-	Negative LVDS differential data input. Channel O0 (odd)
2	RXO0+	Positive LVDS differential data input. Channel O0 (odd)
3	RXO1-	Negative LVDS differential data input. Channel O1 (odd)
4	RXO1+	Positive LVDS differential data input. Channel O1 (odd)
5	RXO2-	Negative LVDS differential data input. Channel O2 (odd)
6	RXO2+	Positive LVDS differential data input. Channel O2 (odd)
7	GND	Ground
8	RXOC-	Negative LVDS differential clock input. (odd)
9	RXOC+	Positive LVDS differential clock input. (odd)
10	RXO3-	Negative LVDS differential data input. Channel O3(odd)
11	RXO3+	Positive LVDS differential data input. Channel O3 (odd)
12	RXE0-	Negative LVDS differential data input. Channel E0 (even)
13	RXE0+	Positive LVDS differential data input. Channel E0 (even)
14	GND	Ground
15	RXE1-	Negative LVDS differential data input. Channel E1 (even)
16	RXE1+	Positive LVDS differential data input. Channel E1 (even)
17	GND	Ground
18	RXE2-	Negative LVDS differential data input. Channel E2 (even)
19	RXE2+	Positive LVDS differential data input. Channel E2 (even)
20	RXEC-	Negative LVDS differential clock input. (even)
21	RXEC+	Positive LVDS differential clock input. (even)
22	RXE3-	Negative LVDS differential data input. Channel E3 (even)
23	RXE3+	Positive LVDS differential data input. Channel E3 (even)
24	GND	Ground
25	NC	Not connecting(should keep open)
26	NC	Not connecting(should keep open)
27	NC	Not connecting(should keep open)
28	VCC	+5.0V power supply
29	VCC	+5.0V power supply
30	VCC	+5.0V power supply

Note (1) Connector Part No.: FI-XB30SRL-HF11(JAE).

Note (2) Mating Connector Part No.:FI-X30H ; FI-X30C* ; FI-X30M* ; FI-X30HL(-T),FI-X30C*L(-T) [JAE]

Note (3) The first pixel is odd.

Note (4) Input signal of even and odd clock should be the same timing.

Version 2.0

Issued Date: Mar. 08, 2006
Model No.: M170E7-L02

Approval

LVDS Channel E0	LVDS output	D7	D6	D4	D3	D2	D1	D0
	Data order	EG0	ER5	ER4	ER3	ER2	ER1	ER0
LVDS Channel E1	LVDS output	D18	D15	D14	D13	D12	D9	D8
	Data order	EB1	EB0	EG5	EG4	EG3	EG2	EG1
LVDS Channel E2	LVDS output	D26	D25	D24	D22	D21	D20	D19
	Data order	DE	NA	NA	EB5	EB4	EB3	EB2
LVDS Channel E3	LVDS output	D23	D17	D16	D11	D10	D5	D27
	Data order	NA	EB7	EB6	EG7	EG6	ER7	ER6
LVDS Channel O0	LVDS output	D7	D6	D4	D3	D2	D1	D0
	Data order	OG0	OR5	OR4	OR3	OR2	OR1	OR0
LVDS Channel O1	LVDS output	D18	D15	D14	D13	D12	D9	D8
	Data order	OB1	OB0	OG5	OG4	OG3	OG2	OG1
LVDS Channel O2	LVDS output	D26	D25	D24	D22	D21	D20	D19
	Data order	DE	NA	NA	OB5	OB4	OB3	OB2
LVDS Channel O3	LVDS output	D23	D17	D16	D11	D10	D5	D27
	Data order	NA	OB7	OB6	OG7	OG6	OR7	OR6

Version 2.0

Issued Date: Mar. 08, 2006
Model No.: M170E7-L02

Approval

5.2 BACKLIGHT UNIT

Pin	Symbol	Description	Remark
1	HV	High Voltage	Pink
2	LV	Low Voltage	White
1	HV	High Voltage	Blue
2	LV	Low Voltage	Black

Note (1) Connector Part No.:JST-BHSR-02VS-1 or equivalent(YEON HO_LOCKING TYPE 35001HS-02L)

Note (2) User's connector Part No.: JST-SM02B-BHSS-1-TB (JST) or equivalent [35001TS-L(YEON HO)]

5.3 COLOR DATA INPUT ASSIGNMENT

The brightness of each primary color (red, green and blue) is based on the 8-bit gray scale data input for the color. The higher the binary input, the brighter the color. The table below provides the assignment of color versus data input.

Color		Data Signal																							
		Red								Green								Blue							
		R7	R6	R5	R4	R3	R2	R1	R0	G7	G6	G5	G4	G3	G2	G1	G0	B7	B6	B5	B4	B3	B2	B1	B0
Basic Colors	Black	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0
	Red	1	1	1	1	1	1	1	1	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0
	Green	0	0	0	0	0	0	0	0	1	1	1	1	1	1	1	1	0	0	0	0	0	0	0	0
	Blue	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	1	1	1	1	1	1	1	1
	Cyan	0	0	0	0	0	0	0	0	1	1	1	1	1	1	1	1	1	1	1	1	1	1	1	1
	Magenta	1	1	1	1	1	1	1	1	0	0	0	0	0	0	0	0	1	1	1	1	1	1	1	1
	Yellow	1	1	1	1	1	1	1	1	1	1	1	1	1	1	1	1	0	0	0	0	0	0	0	0
	White	1	1	1	1	1	1	1	1	1	1	1	1	1	1	1	1	1	1	1	1	1	1	1	1
Gray Scale Of Red	Red(0) / Dark	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0
	Red(1)	0	0	0	0	0	0	0	1	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0
	Red(2)	0	0	0	0	0	0	1	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0
	:	:	:	:	:	:	:	:	:	:	:	:	:	:	:	:	:	:	:	:	:	:	:	:	:
	:	:	:	:	:	:	:	:	:	:	:	:	:	:	:	:	:	:	:	:	:	:	:	:	:
	Red(253)	1	1	1	1	1	1	0	1	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0
	Red(254)	1	1	1	1	1	1	1	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0
	Red(255)	1	1	1	1	1	1	1	1	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0
Gray Scale Of Green	Green(0) / Dark	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0
	Green(1)	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	1	0	0	0	0	0	0	0	0
	Green(2)	0	0	0	0	0	0	0	0	0	0	0	0	0	0	1	0	0	0	0	0	0	0	0	0
	:	:	:	:	:	:	:	:	:	:	:	:	:	:	:	:	:	:	:	:	:	:	:	:	:
	:	:	:	:	:	:	:	:	:	:	:	:	:	:	:	:	:	:	:	:	:	:	:	:	:
	Green(253)	0	0	0	0	0	0	0	0	1	1	1	1	1	1	0	1	0	0	0	0	0	0	0	0
	Green(254)	0	0	0	0	0	0	0	0	1	1	1	1	1	1	1	0	0	0	0	0	0	0	0	0
	Green(255)	0	0	0	0	0	0	0	0	1	1	1	1	1	1	1	1	0	0	0	0	0	0	0	0
Gray Scale Of Blue	Blue(0) / Dark	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0
	Blue(1)	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	1
	Blue(2)	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	1	0
	:	:	:	:	:	:	:	:	:	:	:	:	:	:	:	:	:	:	:	:	:	:	:	:	:
	:	:	:	:	:	:	:	:	:	:	:	:	:	:	:	:	:	:	:	:	:	:	:	:	:
	Blue(253)	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	1	1	1	1	1	1	0	1
	Blue(254)	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	1	1	1	1	1	1	1	0
	Blue(255)	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	0	1	1	1	1	1	1	1	1

Note (1) 0: Low Level Voltage, 1: High Level Voltage

Version 2.0

Issued Date: Mar. 08, 2006
Model No.: M170E7-L02

Approval

6. INTERFACE TIMING

6.1 INPUT SIGNAL TIMING SPECIFICATIONS

The input signal timing specifications are shown as the following table and timing diagram.

| Signal	Item	Symbol	Min.	Typ.	Max.	Unit	Note
LVDS Clock	Frequency	Fc	-	54	67.5	MHz	-
	Period	Tc	14.8	18.5	-	ns	
	High Time	Tch	-	4/7	-	Tc	-
	Low Time	Tcl	-	3/7	-	Tc	-
LVDS Data	Setup Time	Tlvs	600	-	-	ps	-
	Hold Time	Tlvh	600	-	-	ps	-
Vertical Active Display Term	Frame Rate	Fr	56	60	75	Hz	Tv=Tvd+Tvb
	Total	Tv	1034	1066	1274	Th	-
	Display	Tvd	1024	1024	1024	Th	-
	Blank	Tvb	Tv-Tvd	42	Tv-Tvd	Th	-
Horizontal Active Display Term	Total	Th	690	844	960	Tc	Th=Thd+Thb
	Display	Thd	640	640	640	Tc	-
	Blank	Thb	Th-Thd	204	Th-Thd	Tc	-

Note: (1) Because this module is operated by DE only mode, Hsync and Vsync input signals should be set to low logic level or ground. Otherwise, this module would operate abnormally.

INPUT SIGNAL TIMING DIAGRAM

Version 2.0

Issued Date: Mar. 08, 2006
Model No.: M170E7-L02

Approval

6.2 POWER ON/OFF SEQUENCE

To prevent a latch-up or DC operation of LCD module, the power on/off sequence should follow the conditions shown in the following diagram.

Power ON/OFF Sequence

Note.

(1) The supply voltage of the external system for the module input should be the same as the definition of Vcc.

(2) Please apply the lamp voltage within the LCD operation range. When the backlight turns on before the LCD operation of the LCD turns off, the display may, instantly, function abnormally.

(3) In case of VCC = off level, please keep the level of input signals on the low or keep a high impedance.

(4) T4 should be measured after the module has been fully discharged between power on/off periods.

(5) Interface signal shall not be kept at high impedance when the power is on.

Version 2.0

Issued Date: Mar. 08, 2006
Model No.: M170E7-L02

Approval

7. OPTICAL CHARACTERISTICS

7.1 TEST CONDITIONS

Item	Symbol	Value	Unit
Ambient Temperature	Ta	25±2	^{o}C
Ambient Humidity	Ha	50±10	%RH
Supply Voltage	V_{CC}	5.0	V
Input Signal	According to typical value in "3. ELECTRICAL CHARACTERISTICS"		
Inverter Current	I_L	7.0	mA
Inverter Driving Frequency	F_L	61	KHz
Inverter	SUMIDA H05-5307		

7.2 OPTICAL SPECIFICATIONS

The relative measurement methods of optical characteristics are shown in 7.2. The following items should

be measured under the test conditions described in 7.1 and stable environment shown in Note (5).

Item		Symbol	Condition	Min.	Typ.	Max.	Unit	Note
Color Chromaticity (CIE 1931)	Red	Rx	$\theta_x=0°, \theta_Y=0°$ CS-1000T R=G=B=255 Grayscale	Typ. -0.03	0.647	Typ. +0.03	---	(1), (5)
		Ry			0.332			
	Green	Gx			0.284			
		Gy			0.608			
	Blue	Bx			0.149			
		By			0.067			
	White	Wx			0.313			
		Wy			0.329			
Center Luminance of White		L_w		250	300	---	cd/m^2	(4), (5)
Contrast Ratio		CR		600	800	---	-	(2), (5)
Response Time		T_R	$\theta_x=0°, \theta_Y=0°$	---	1	6	ms	(3)
		T_F		---	4	9		
Luminance Uniformity (9 points)		δW	$\theta_x=0°, \theta_Y=0°$ CA210	---	1.25	1.40	-	(5), (6)
Viewing Angle	Horizontal	θ_x+	CR $\geqq$ 10 BM-5A	75	85	---	Deg.	(1), (5)
		θ_x-		75	85	---		
	Vertical	θ_Y+		70	80	---		
		θ_Y-		70	80	---		

Version 2.0

Approval

Note (1) Definition of Viewing Angle (θx, θy):

Note (2) Definition of Contrast Ratio (CR):

The contrast ratio can be calculated by the following expression.

Contrast Ratio (CR) = L_w / L_d

L_w: Luminance of gray level 255

L_d: Luminance of gray level 0

CR = CR (5)

CR (X) is corresponding to the Contrast Ratio of the point X at Figure in **Note (6).**

Note (3) Definition of Response Time (T_R, T_F) and measurement method:

Version 2.0

Issued Date: Mar. 08, 2006
Model No.: M170E7-L02

Approval

Note (4) Definition of Luminance of White (L_w) :

Measure the luminance of gray level 255 at center point

L_w = L (5)

L (x) is corresponding to the luminance of the point X at Figure in **Note (6).**

Note (5) Measurement Setup:

The LCD module should be stabilized at given temperature for **15 minutes** to avoid abrupt temperature change during measuring. In order to stabilize the luminance, the measurement should be executed after lighting Backlight for **15 minutes** in a windless room.

LCD Module

LCD Panel

Center of the Screen

TOPCON/BM-5A
MINOLTA /CA210
MINOLTA /CS-1000T

Field of View = 2º

500 mm

Light Shield Room
(Ambient Luminance < 2 lux)

Version 2.0

Approval

Note (6)   Definition of Luminance Uniformity (δW):

Measure the luminance of gray level 255 at 9 points

$$\delta W = \frac{\text{Maximum } [L(1), L(2), L(3), L(4), L(5), L(6), L(7), L(8), L(9)]}{\text{Minimum } [L(1), L(2), L(3), L(4), L(5), L(6), L(7), L(8), L(9)]}$$

Horizontal Line

Active Area

Version 2.0

Issued Date: Mar. 08, 2006
Model No.: M170E7-L02

Approval

8. PACKAGING

8.1 PACKING SPECIFICATIONS

(1) 5 LCD modules / 1 Box

(2) Box dimensions: 470(L) X 268(W) X 430(H) mm

(3) Weight: approximately 10.5 Kg (5 modules per box)

8.2 PACKING METHOD

(1) Carton Packing should have no failure in the following reliability test items.

| Test Item	Test Conditions	Note
Vibration	ISTA STANDARD Random, Frequency Range: 1 – 200 Hz Top & Bottom: 30 minutes (+Z), 10 min (-Z), Right & Left: 10 minutes (X) Back & Forth 10 minutes (Y)	Non Operation
Dropping Test	1 Angle, 3 Edge, 6 Face, 60cm	Non Operation

Box Dimensions: 470(L)x268(W)x430(H) mm
Weight:Approx. 10.5kg (5 module. per.1box)

Figure. 8-1 Packing method

Version 2.0

Approval

For ocean shipping

Pallet:L1100*W970*H135mm
Pallet Stock Dim:L1100*W970*H1865mm
Weight:Appprox. 364kg

PE Sheet

Corner Protector
L800*50*50mm

Corner Protector
L1650*50*50mm

Film

PP Belt

Pallet

Carton Label

Figure. 8-2 Packing method

For air transport

Pallet:L1100*W970*H135mm
Pallet Stock Dim:L1100*W970*H1435mm
Weight:Appprox. 280kg

PE Sheet

Corner Protector
L1170*50*50mm

Corner Protector
L800*50*50mm

Film

PP Belt

Pallet

Carton Label

Figure. 8-3 Packing method

**Version 2.0**

Issued Date: Mar. 08, 2006
Model No.: M170E7-L02

Approval

9. DEFINITION OF LABELS

9.1 CMO MODULE LABEL

The barcode nameplate is pasted on each module as illustration, and its definitions are as following explanation.

(a) Model Name: M170E7-L02

(b) Revision: Rev. XX, for example: A0, A1… B1, B2… or C1, C2…etc.

(c) CMO barcode definition:

Serial ID: XX-XX-X-XX-YMD-L-NNNN

Code	Meaning	Description
XX	CMO internal use	-
XX	Revision	Cover all the change
X	CMO internal use	-
XX	CMO internal use	-
YMD	Year, month, day	Year: 2001=1, 2002=2, 2003=3, 2004=4… Month: 1~12=1, 2, 3, ~, 9, A, B, C Day: 1~31=1, 2, 3, ~, 9, A, B, C, ~, W, X, Y, exclude I, O, and U.
L	Product line #	Line 1=1, Line 2=2, Line 3=3, …
NNNN	Serial number	Manufacturing sequence of product

(d) Customer's barcode definition:

Serial ID: CM-17E72-X-X-X-XX-L-XX-L-YMD-NNNN

| Code	Meaning	Description
CM	Supplier code	CMO=CM
17E72	Model number	M170E7-L02 = 17E72
X	Revision code	Non ZBD: 1,~,9,0 / ZBD: A~Z
X	Source driver IC code	Century=1, CLL=2, Demos=3, Epson=4, Fujitsu=5, Himax=6, Hitachi=7, Hynix=8, LDI=9, Matsushita=A, NEC=B, Novatec=C, OKI=D, Philips=E, Renasas=F, Samsung=G, Sanyo=H, Sharp=I, TI=J, Topro=K, Toshiba=L, Windbond=M
X	Gate driver IC code	
XX	Cell location	Tainan Taiwan=TN, Ningbo China=CN
L	Cell line #	1~12=0~C
XX	Module location	Tainan Taiwan=TN, Ningbo China=CN
L	Module line #	1~12=0~C
YMD	Year, month, day	Year: 2001=1, 2002=2, 2003=3, 2004=4… Month: 1~12=1, 2, 3, ~, 9, A, B, C Day: 1~31=1, 2, 3, ~, 9, A, B, C, ~, T, U, V
NNNN	Serial number	By LCD supplier

Version 2.0

Approval

10. PRECAUTIONS

10.1 ASSEMBLY AND HANDLING PRECAUTIONS

(1) Do not apply rough force such as bending or twisting to the module during assembly.

(2) To assemble or install module into user's system can be only in clean working areas. The dust and oil may cause electrical short or worsen the polarizer.

(3) It's not permitted to have pressure or impulse on the module because the LCD panel and Backlight will be damaged.

(4) Always follow the correct power sequence when LCD module is connecting and operating. This can prevent damage to the CMOS LSI chips during latch-up.

(5) Do not pull the I/F connector in or out while the module is operating.

(6) Do not disassemble the module.

(7) Use a soft dry cloth without chemicals for cleaning, because the surface of polarizer is very soft and easily scratched.

(8) It is dangerous that moisture come into or contacted the LCD module, because moisture may damage LCD module when it is operating.

(9) High temperature or humidity may reduce the performance of module. Please store LCD module within the specified storage conditions.

(10) When ambient temperature is lower than 10ºC may reduce the display quality. For example, the response time will become slowly, and the starting voltage of CCFL will be higher than room temperature.

10.2 SAFETY PRECAUTIONS

(1) The startup voltage of Backlight is approximately 1000 Volts. It may cause electrical shock while assembling with inverter. Do not disassemble the module or insert anything into the Backlight unit.

(2) If the liquid crystal material leaks from the panel, it should be kept away from the eyes or mouth. In case of contact with hands, skin or clothes, it has to be washed away thoroughly with soap.

(3) After the module's end of life, it is not harmful in case of normal operation and storage.

Version 2.0

2-M3 USER HOLE

12.67 ±0.5
2-7.8 ±0.3
(20.67)
1245 ±0.3
249±0.3

354.92 ±0.5 (CUT LINE)
340.92 (BEZEL OPEN)
337.92 (ACTIVE AREA)

15 ±0.5

Active Area

1.5 ±0.5

270.336 (ACTIVE AREA)
273.336 (BEZEL OPEN)
290.336 ±0.5 (CUT LINE)

2-M3 USER HOLE
2-7.8 ±0.3
(16.57)
128.6 ±0.3
257.2 ±0.3

NOTES:
1. OUTLINE TOLERANCE: ±0.5mm.
2. "*" MARKS THE DESIGN CRITICAL DIMENSION.
3. "ⓟ" MARKS THE PROCESS CRITICAL DIMENSION.
4. MAX.SCREW LENGTH:4.3 mm.
5. MAX.SCREW TORQUE:4 kg-cm.
6. I/F CONNECTOR FI-XB30SR(JAE) OR EQUIVALENT
7. LAMP CONNECTOR/WIRE :JST BHSR-02VS-1 OR EQUIVALENT

SECTION A-A
SCALE 5:1

0.6
0.6

4.3 (MAX)

4-M3 TAP
LENGTH 4.3mm MAX
TORQURE:4kgf-cm MAX

TITLE	ASSY_MODULE_M070E7	
Approved	JEMMY_CHANG	Drawing No. M070741000
Checked	ROCKY_YANG	Part No. TBD
Drawer	ICE_RED	Material TBD
Designer	ICE_RED	Date 23-Feb-2005 Scale 1:1 Unitmm

2D REV.
3D REV.L137+

Sheet 1 / 2 A1

Mark	Description	Date	Changed_By	Approved_By	ECN No.	Remark

COLD CATHODE FLUORESCENT LAMP IN LCD PANEL CONTAINS A SMALL AMOUNT OF MERCURY PLEASE FOLLOW LOCAL ORDINANCES OR REGULATIONS FOR DISPOSAL.

2D REV.	1.1+	
3D REV.	1.37+	
Sheet	2 / 2	A2

TITLE	ASSY_MODULE_M170E7	
Approved	JEMMY_CHANG	Drawing No.	M170741101
Checked	ROCKY_YANG	Part No.	TBD
Drawer	ICE_RED	Material	TBD
Designer	ICE_RED	Date	06-Jan-2005	Scale	1:1	Unit:mm

CHI MEI
OPTOELECTRONICS CORP.

ALL RIGHTS RESERVED, COPYING FORBIDDEN.

Mark	Description	Date	Changed_By	Approved_By	ECN No.	Remark

101.62

144.2

144.2

47.7

PIN 1

2-θ15GΠΠLED

M170Ex -XXX Rev.A1

56±3

56±3

100±5

100±5